



Thank you for giving UL the opportunity to partner with you.

Please note, Follow-Up Procedure Revisions or Report Revisions do not include Authorization Pages, Indices, Section General, and/or Appendices unless revisions were required or requested.

Should you have any questions, after reviewing the material, or need to report any inaccuracies, please reach out to your UL representative or find UL contact details for your local Customer Service Department at <https://www.ul.com/about/locations>.

Please find attached the related material on Project

For your convenience, the below describes the related updates:

E158873-A6227-DescriptionUL
Figure-11-Total

This material is provided on behalf of UL LLC (UL) or any authorized licensee of UL.

Times change, Trust Remains™

UL TEST REPORT AND PROCEDURE

Standard:	UL 62368-1, 3rd Ed, 2021-10-22 (Audio/video, information and communication technology equipment Part 1: Safety requirements) CAN/CSA C22.2 No. 62368-1:19, 3rd Ed, 2021-10-22 (Audio/video, information and communication technology equipment Part 1: Safety requirements)
Certification Type:	Listing
CCN:	AZOT, AZOT7 (Audio/video, Information and Communication Technology Equipment)
Complementary CCN:	N/A
Product:	NETWORK CAMERA
Model:	TNV-C8014RM, TNV-C8034RM
Rating:	PoE (48 Vdc), 0.15 A
Applicant Name and Address:	HANWHA VISION CO LTD 6, PANGYO-RO 319BEON-GIL, BUNDANG-GU SEONGNAM-SI GYEONGGI-DO 13488 KOREA

This is to certify that representative samples of the products covered by this Test Report have been investigated in accordance with the above referenced Standards. The products have been found to comply with the requirements covering the category and the products are judged to be eligible for Follow-Up Service under the indicated Test Procedure. The manufacturer is authorized to use the UL Mark on such products which comply with this Test Report and any other applicable requirements of UL LLC ('UL') in accordance with the Follow-Up Service Agreement. Only those products which properly bear the UL Mark are considered as being covered by UL's Follow-Up Service under the indicated Test Procedure.

The applicant is authorized to reproduce the referenced Test Report provided it is reproduced in its entirety.

UL authorizes the applicant to reproduce the latest pages of the referenced Test Report consisting of the first page of the Specific Technical Criteria through to the end of the Conditions of Acceptability.

Any information and documentation involving UL Mark services are provided on behalf of UL LLC (UL) or any authorized licensee of UL.

Prepared By: Lawrence Lee / Project Handler Reviewed By: HanQ Choi / Reviewer

Supporting Documentation

The following documents located at the beginning of this Procedure supplement the requirements of this Test Report:

A. Authorization - The Authorization page may include additional Factory Identification Code markings.

B. Generic Inspection Instructions -

- i. Part AC details important information which may be applicable to products covered by this Procedure. Products described in this Test Report must comply with any applicable items listed unless otherwise stated in the body of this Test Report.
- ii. Part AE details any requirements which may be applicable to all products covered by this Procedure. Products described in this Test Report must comply with any applicable items listed unless otherwise stated in the body of each Test Report.
- iii. Part AF details the requirements for the UL Certification Mark which is not controlled by the technical standard used to investigate these products. Products are permitted to bear only the Certification Mark(s) corresponding to the countries for which it is certified, as indicated in each Test Report.

Product Description

NETWORK CAMERA is designed for outdoor or indoor use, wall or ceiling use with mounting brackets.

It is a commercial equipment supplied from UL listed PoE (Power over Ethernet) input and installed by service personnel.

Model Differences

TNV-C8014RM is basic model.

TNV-C8034RM is identical to basic model except model designation.

Test Item Particulars

Product group	end product
Classification of use by	Instructed person
Supply Connection	not mains connected: ES1
Supply tolerance	None
Supply connection – type	PoE (Power over Ethernet)
Considered current rating of protective device	N/A
Equipment mobility	wall/ceiling-mounted
Over voltage category (OVC)	OVC I
Class of equipment	Class III
Special installation location	Outdoor location
Pollution degree (PD)	PD 2
Manufacturer's specified T _{ma} (°C)	55 Outdoor: minimum -40
IP protection class	IP 66
Power systems	not AC mains
Altitude during operation (m)	2000 m or less
Altitude of test laboratory (m)	2000 m or less
Mass of equipment (kg)	0.466

Technical Considerations

- ☐ The product was submitted and evaluated for use at the maximum ambient temperature (T_{ma}) permitted by the manufacturer's specification of : 55 °C
- ☐ The product is intended for use on the following power systems : No direct connection
- ☐ Considered current rating of protective device as part of the building installation (A) : N/A
- ☐ Mains supply tolerance (%) or absolute mains supply : No direct connection
- ☐ The Risk Group of a lamp or lamp system (including LEDs) is : Exempt
- ☐ The following are available from the Applicant upon request : Installation (Safety) Instructions / Manual
- ☐ The outdoor equipment/enclosure was evaluated for use in an ambient range of : -40 °C to 55 °C

Additional Information

4791512284

- Maximum Normal Load: Continuous operation (Operate the camera through networked equipment with IR LED on.)

4791599121

- [CCL] Add type information for Opto-coupler (LS201); (Type: LTV-217-C-G).

- [CCL] Correct type information for Gasket for Top from O-VMQ-50-GR to O-VMQ-50-BK.

Additional Standards

The product fulfills the requirements of: IEC 62471:2006

Markings and Instructions

Clause Title	Marking or Instruction Details
Equipment identification marking – Manufacturer identification	Listee's or Recognized Company's name, Trade Name, File Number
Equipment identification marking – model identification	Model Number
Equipment rating marking – ratings	Input Ratings (voltage, current)
Outdoor enclosure type	"Rainproof", IP66
Hard Copy	A. IMPORTANT or ATTENTION or similar wording B. Please check 'Manuals' from our website, before connecting to the supply. C. Company website URL (https://www.~~) or QR code.
(Website) Manual - 1	This product is intended to be supplied by a UL Listed Power Supply Unit marked "Class 2" or "LPS" or "PS2" and rated from PoE (48 Vdc), 0.15 A.
(Website) Manual - 2	The wired LAN hub providing power over the Ethernet (PoE) in accordance with IEEE 802.3.af shall be a UL Listed device with the output evaluated as a Limited Power Source as defined in UL 60950-1 or PS2 as defined in UL 62368-1.

Special Instructions to UL Representative

Issue Date: 2024-12-04

Page 4 of 9

Report Reference #

E158873-A6227-UL

Revision Date: 2024-12-18

N/A

BD1.0	TABLE: Production-Line Testing Requirements					
BD1.1	Electric Strength Test Special Constructions – Refer to Generic Inspection Instructions, Part AC for further information.					
Model	Component	Removable parts	Test probe location	Test V rms	Test V dc	Test Time, s
N/A	N/A	N/A	N/A	N/A	N/A	N/A
BD1.2	Earthing Continuity Test Exemptions – This test is not required for the following models:					
	All model					
BD1.3	Electric Strength Test Exemptions – This test is not required for the following models:					
	All model					
BD1.4	Electric Strength Test Component Exemptions – The following solid-state components may be disconnected from the remainder of the circuitry during the performance of this test.					
	All model					

BE1.0	Sample and Test Specifics for Follow-Up Tests at UL				
Model	Component	Material	Test	Sample (s)	Test Specifics
N/A	N/A	N/A	N/A	N/A	N/A

4.1.2	TABLE: List of critical components					Pass
Object / part No.	Manufacturer/ trademark	Type / model	Technical data	Product Category CCN(s)	Mark(s) of conformity	Supplement ID
Enclosure - Case (Metal)	Interchangeable	Interchangeable	Aluminum, Min. 1.5 mm thickness.	-	-	
Enclosure - Case (Plastic)	mitsubishi ENGINEERING- PLASTICS CORP	S-2000+(f1)	Min. 1.5 mm thickness, rated Min. V-2, 125 deg. C	QMFZ2	UL (E41179)	
Internal Plastic	LOTTE CHEMICAL CORPORATION	HN-1068(+)(f1)	Min. 1.5 mm thickness, rated Min. V-0, 130 deg. C	QMFZ2	UL (E115797)	
Internal (Plastic) - Alternate	Interchangeable	Interchangeable	Min. 1.5 mm thickness, rated Min. HB	-	-	
Opto-coupler (LS201)	LITE-ON TECHNOLOGY CORP	LTV-217 (Type: LTV-217-C-G)	Isolation Voltage: 3750. Max. Operation Temperature:110 deg. C	FPQU2/8	UL (E113898)	
Opto-coupler (LS201) -Alternate	COSMO ELECTRONICS CORP	KPC357NT	Isolation Voltage: 3750. Max. Operation Temperature: 115 deg. C	FPQU2/8	UL (E169586)	
Transformer (T1)	SHENZHEN GROUP-TEK ELECTRONICS TECHNOLOGY CO. , LTD	PDT2431SR	115 uH, 130 deg. C, See enclosure for more detail.	-	-	
Line Filter (L12)	3L ELECTRONIC (ZHONG SHAN) CORP.	SMTLF3922P- 472N-0.5A	4.7 mH, 125 deg, See enclosure for more detail.	-	-	
Lens module (TNV-C8014RM)	SUNNY OPTICS(ZHONGSH AN) CO LTD	C7304E-28H	Rated 3.0 - 6.0 Vdc	-	-	








Lens module (TNV-C8034RM)	UNION OPTECH CO LTD	T3123-A51	Rated 3.5 - 12.0 Vdc	-	-	
Rechargeable battery (BAT1)	SEIKO INSTRUMENTS INC MICRO-ENERGY DIV	ML414H	Lithium, Rechargeable, Max Charging Voltage, 3.4 V dc, Max Charging current: 300 mA	BBCV2	UL (MH15628)	
Lithium Battery Protection Circuit (BAT1)	Interchangeable	Interchangeable	Diode (D1, 85 V, 300 mA) and Resistor (R55, 3.3 Kohm) in series	-	-	
Thermal pad	KOMOTECH	KGP-1(a)	Min.0.2 mm thickness, rated V-0, 105 deg. C	QMFZ2	UL (E245303)	
Thermal pad - Alternate	ATEKS CO LTD	ATP-20	Min.0.2 mm thickness, rated V-0, 105 deg. C	QMFZ2	UL (E513170)	
PWB	HANNSTAR BOARD CORP	MV-4	Min. V-0, 130 deg. C	ZPMV2	UL (E89382)	
PWB - Alternate	Interchangeable	Interchangeable	Min. V-0, 130 deg. C	ZPMV2	UL	
Gasket for Dome	Namyang Vina	O-VMQ-50-BK	Gasket Test was conducted under E158873-A6034	-	-	
Gasket for Window-IR	Y&K TECH CO LTD	O-VMQ-50-GR	Gasket Test was conducted under E158873-A6034	-	-	
Gasket for Top	Y&K TECH CO LTD	O-VMQ-50-BK	Gasket Test was conducted under E158873-A6034	-	-	
Outdoor Label	Interchangeable	Interchangeable	Suitable for use on each type of surface to which applied, rated for maximum and minimum surface temperature specified, or Min. 55 deg. C to Max -40 deg. C if not specified.	PGDQ2 or PGJI2	UL	

LED (LD1, LD2)	CYBRIGHT IR LED TECHNOLOGY CO.,LTD	XB-IR3838EU-I	VF = Max. 2.3 V, IF= Max. 1 A	-	-	
----------------	--	---------------	----------------------------------	---	---	--

Enclosures

Type	Supplement Id	Description
Photographs	03-01	External View
Photographs	03-02	Internal View
Photographs	03-04	Lens Module
Photographs	03-05	LED Board
Photographs	03-06	Network Board - Top
Photographs	03-07	Network Board - Bottom
Photographs	03-08	Label
Diagrams	04-01	Diagrams
Manuals	06-01	Manual
Miscellaneous	07-01	Transformer (T1) Specification
Miscellaneous	07-02	Line Filter (L12) Specification

The following Page(s) are related to Diagrams-01. The next supplement, if applicable, will be identified with a new Supplement Page Heading.



3	MODEL 2	
2	MODEL 1	
1	TNV-C8014RM/C8034RM	'24.08.22
No.	MODEL NAME	DATE
Unit:mm[inch] SCALE:1/1		Hanwha Vision

The following Page(s) are related to Manuals-01. The next supplement, if applicable, will be identified with a new Supplement Page Heading.

IMPORTANT SAFETY INSTRUCTIONS

1. Read these instructions.
2. Keep these instructions.
3. Heed all warnings.
4. Follow all instructions.
5. Do not use this apparatus near water.
6. Clean the contaminated area on the product surface with a soft, dry cloth or a damp cloth.
(Do not use a detergent or cosmetic products that contain alcohol, solvents or surfactants or oil constituents as they may deform or cause damage to the product.)
7. Do not block any ventilation openings, Install in accordance with the manufacturer's instructions.
8. Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
9. Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
10. Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
11. Only use attachments/ accessories specified by the manufacturer.
12. Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/ apparatus combination to avoid injury from tip-over.
13. Unplug this apparatus during lighting storms or when unused for long periods of time.
14. Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.
15. This product is intended to be supplied by a UL Listed Power Supply Unit marked "Class 2" or "LPS" or "PS2" and rated from PoE (48Vdc), 0.15A.
16. This product is intended to be supplied by isolation power.
17. If you use excessive force when installing the product, the camera may be damaged and malfunction.
If you forcibly install the product using non-compliant tools, the product may be damaged.
18. Do not install the product in a place where chemical substances or oil mist exists or may be generated. As edible oils such as soybean oil may damage or warp the product, do not install the product in the kitchen or near the kitchen table.
This may cause damage to the product.
19. When installing the product, be careful not to allow the surface of the product to be stained with chemical substance.
Some chemical solvents such as cleaner or adhesives may cause serious damage to the product's surface.



20. If you install/disassemble the product in a manner that has not been recommended, the production functions/ performance may not be guaranteed.
Install the product by referring to "Installation & connection" in the user manual.
21. Installing or using the product in water can cause serious damage to the product.
22. Although a rapid change in temperature could cause frost inside the dome, there will be no problem with the video.
23. The operating temperature for the TNV-C8014RM/TNV-C8034RM products is -40°C to +55°C (-40°F to +131°F).

WARNING

TO REDUCE THE RISK OF FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE THIS PRODUCT TO RAIN OR MOISTURE. DO NOT INSERT ANY METALLIC OBJECT THROUGH THE VENTILATION GRILLS OR OTHER OPENINGS ON THE EQUIPMENT.

Apparatus shall not be exposed to dripping or splashing and that no objects filled with liquids, such as vases, shall be placed on the apparatus.

To prevent injury, this apparatus must be securely attached to the Wall/ceiling in accordance with the installation instructions.

CAUTION

	CAUTION RISK OF ELECTRIC SHOCK. DO NOT OPEN	
CAUTION : TO REDUCE THE RISK OF ELECTRIC SHOCK. DO NOT REMOVE COVER (OR BACK). NO USER SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.		

EXPLANATION OF GRAPHICAL SYMBOLS



The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the product.

Class I construction

An apparatus with CLASS I construction shall be connected to a MAINS socket outlet with a protective earthing connection.

Battery

Batteries(battery pack or batteries installed) shall not be exposed to excessive heat such as sunshine, fire or the like.

The battery cannot be replaced.

Prohibition of battery abuse

- Do not install and use the wrong type of battery.
- Do not leave the battery in a mechanically crush or cut it because it can explode.
- Do not leave the battery in a high temperature environment.
- Do not leave the battery in a low-pressure environment.

Disconnection Device

Disconnect the main plug from the apparatus, if it's defected. And please call a repair man in your location.

When used outside of the U.S., it may be used HAR code with fittings of an approved agency is employed.

CAUTION

RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE.
DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS.

ATTENTION

IL Y A RISQUE D'EXPLOSION SI LA BATTERIE EST REMPLACÉE PAR UNE BATTERIE DE TYPE INCORRECT.
METTRE AU REBUT LES BATTERIES USAGÉES CONFORMÉMENT AUX INSTRUCTIONS.

CAUTION

These servicing instructions are for use by qualified service personnel only.
To reduce the risk of electric shock do not perform any servicing other than that contained in the operating instructions unless you are qualified to do so.

Please use the input power with just one camera and other devices must not be connected.

The Micro USB port on the product is intended for initial setup only and should not be used for any other purpose.

When a new product box is opened (or during the initial use of the product), moisture might build up on the glass of the camera. The built-up moisture disappears naturally within a few hours after powered on.

The ITE is to be connected only to PoE networks without routing to the outside plant.

The wired LAN hub providing power over the Ethernet (PoE) in accordance with IEEE 802.3af shall be a UL Listed device with the output evaluated as a Limited Power Source as defined in UL60950-1 or PS2 as defined in UL62368-1.

Unit is intended for installation in a Network Environment 0 as defined in IEC TR 62102. As such, associated Ethernet wiring shall be limited to inside the building.

Please read the following recommended safety precautions carefully.

- Do not place this apparatus on an uneven surface.
- Do not install on a surface where it is exposed to direct sunlight, near heating equipment or heavy cold area.
- Do not place this apparatus near conductive material.
- Do not attempt to service this apparatus yourself.
- Do not place a glass of water on the product.
- Do not install near any magnetic sources.
- Do not block any ventilation openings.
- Do not place heavy items on the product.
- Please wear protective gloves when installing/removing the camera.
The high temperature of the product surface may cause a burn.

User's Manual is a guidance book for how to use the products.

The meaning of the symbols are shown below.

- Reference : In case of providing information for helping of product's usages
- Notice : If there's any possibility to occur any damages for the goods and human caused by not following the instruction




※ Please read this manual for the safety before using of goods and keep it in the safe place.

We do not guarantee the quality of third-party products (e.g. lenses, accessories) that you separately purchase.

In particular installation environments, there might be interference in radio communications. When interference of electromagnetic waves occurs between the product and radio communication device, it is recommended to keep a certain distance between the two or change the direction of the receiving antenna.


WHAT'S INCLUDED

As for each sales country, accessories are not the same.



■ Use installation screws of at least M4, L30 for the installation of this product.

AT A GLANCE



INSTALLATION


Precautions before installation

Ensure you read out the following instructions before installing the camera:

- Select an installation site that can hold at least 5 times the camera's weight.
- Stuck-in or peeled-off cables can cause damage to the product or a fire.
- For safety purposes, keep anyone else away from the installation site. And put aside personal belongings from the site, just in case.
- If the product is installed with excessive force, it may cause damage to the camera due to malfunction. Forcing assembly using non-compliant tools may damage the product.
- This camera is a waterproof product that meets IP66 standards. However, if the M12 standard connector and cable are not used, the jack part will not be waterproof. It is recommended to use an M12 standard external cable when installing this product.


Removal

1. Remove the dome cover by turning the dome cover's fastening screws counterclockwise.
 - It is not required to completely remove screws from the cover.



Inserting a Micro SD card


Insert the micro SD card into the micro SD card slot on the camera body in the arrow direction.



- Before installing the camera, the Micro SD card should be inserted while the power source and the body are separated.
- Do not forcefully insert it in the reverse direction. It might damage your Micro SD card and your product.
- When it rains or the humidity is high, insertion or ejection of a Micro SD card is not recommended.
- When installing/removing the Micro SD card, make sure you put the product body on a flat ground before working on it in order to prevent accidents due to loss or drop of any parts.
- Disassembly of the product cover should be finished within 5 minutes, or there will be the risk of internal dew condensation.

Removing a Micro SD card

Gently press down on the exposed end of the Micro SD card as shown in the diagram to eject the Micro SD card from the slot.




- Before removing the Micro SD card, in <Setup (⚙️)>><Event>><Storage>, set the device to <Off> and press the [Apply] button and turn the camera off.
- If you turn off the camera or remove the Micro SD card that contains data from the product, the data may be lost or damaged.


Installation

[Directly installing on wall/ceiling]

1. Place the camera body on the desired location considering the direction to be monitored, mark the locations for the screw holes, and then drill the holes.




2. Fix the camera body using appropriate screws.
 - It must be installed on the area (ceiling or wall) that can withstand 5 times the weight of the camera including the installation bracket.




3. Insert the external M12 male connector into the M12 female connector connection groove of the camera.
4. Turn the screws on both sides of the camera lens fixing cover counterclockwise to loosen them.

! ■ Forcing to tilt the lens (hood) without loosening the screws may cause a product defect.



5. Adjust the lens to the desired direction with reference to "Adjusting the monitoring direction for the camera" section. (page 11)
 - If you tilt the lens, you may need to adjust the lens as this may block the screen.
 - Connect a monitoring device to the USB port and then monitor and adjust it. (page 13)
6. When adjusting lens direction is complete, fix the lens angle by turning the screws clockwise.




Assembling the dome cover

[Directly installing on wall/ceiling]


1. Assemble the dome cover.

! ■ Make sure to firmly tighten the fastening screws so that there is no water damage issue.



The following Page(s) are related to Miscellaneous-01. The next supplement, if applicable, will be identified with a new Supplement Page Heading.

2. Mechanical Dimensions:



Note:


1. Wrap 2Ts of 6mm tape around the finished part.

Unit: mm

A MAX	B MAX	C MAX	D TYP
12.7	11.43	15.24	10.60

SUGGESTED PAD LAYOUT

Unit: mm Tolerances: +/-0.2



3. Electrical Characteristics :


Specifications Test: at 25 °C. Operating Temperature: -40 to +125°C			
NO.	ITEM	TEST CONDITION	SPECIFICATION
1	Inductance	(3-4)@200kHz, 0.1v	155uH+/-10%.
2	Inductance	(2-1)@200kHz, 0.1v	30uH+/-15%.
3	Inductance	(7-5)///(8-6)@200kHz, 0.1v	5.3uH+/-15%.
4	Leakage Inductance	(3-4) with shorted other@200kHz, 0.1v	3.6uH MAX.
5	DCR	(3-4) @ 25°C	0.414 Ω Max.
6		(7+8)-(5+6) @ 25°C	0.06Ω Max.
7		(2-1) @ 25°C	0.822Ω Max.
8	HI-POT	PRI TO SEC	1500Vac 1mA 3Sec.
9	T/R	(3-4):(9+10-7+8):(2-1)	33:6:14±2%.

5.Winding Information:


WINDING SEQ.	ST-FN	WIRE/FOIL	TURNS	WRAP INSUL.	MARGIN TAPE	SLEEVE	NOTE
1	3--4	0.30mm 2UEW	33	2T w6.0mm	N/A	N/A	1
2	8--6 7--5	0.30mm 2UEW R 0.30mm 2UEW N	6	2T w6.0mm	2T W0.80mm	N/A	1
3	2--1	0.23mm 2UEW	14	2T w6.0mm	2T W0.80mm	N/A	1

NOTE :
1. -Place the bobbin pin 1 right side of operator.

6.Schematic:



7.Winding construction



8.Material List


NO.	ITEM.	MATERIALS	SUPPLIERS/MANUFACTURERS	UL FILE NO.
1	BOBBIN	PHENOLIC T375J UL RATING: 94V-0	CHANG CHUN PLASTIC CO LTD.	QMFZ2.E59481
2	CORE	Ep10 PG232A	High-tech Electronics Co.,Ltd.	N/A
3	WIRE	POLYURETHANE ENAMELED TYPE NO: 2UEW 0.23mm 0.30mm THERMAL RATING:180°C	Shing Shun Magnet wire(HuiZhou) Co.,Ltd	E255839
4	TAPE	ADHESIVE POLYESTER TAPE TYPE NO.:CT*(c)(g) THERMAL RATING:130°C yellow tape: for inner coils	JingJiang yahua pressure sensitive glue Co.,Ltd	E165111
5	TAPE	ADHESIVE POLYESTER TAPE TYPE NO.:519(kapton tape) THERMAL RATING:200°C Kapton tape: for outside of core	Shen zhen yanda electronic Technology Co.,Ltd	E309332
6	SOLDER	SN/CU: 99.3/0.7	Gao Xin stannum industry Co.,Ltd	N/A
7	Glue	E-500(xx)	Dong Guan city eatto electronic material Co.,Ltd	E218090
8	INK	VIC-120	Shenshen Huarui samwo group Co.,Ltd	N/A

9.PACKING INFORMATION:

DESCRIPTION	QTY
PIECES PER REEL	250
PIECES PER POCKET	1
PIECES PER BOX	750
REEL PER BOX	3
GROSS WEIGHT PER BOX(KG)	TBD
NET WEIGHT PER BOX(KG)	TBD

外形和尺寸

OUTLINE AND DIMENSIONS



A : 11.50 ± 0.3

2B : 10.2 ± 0.2

E : 3.30 ± 0.15

C : 7.65 ± 0.2

D : 9.40 ± 0.2


2F : 7.40 ± 0.20

磁芯常数 Core Factor C1 (mm ⁻¹)	有效磁路长度 Effective Length Le (mm)	有效横截面积 Effective Area Ae (mm ²)	有效体积 Effective Volume Ve (mm ³)	重量 Weight (g/set)
1.70	18.60	11.30	213.6	2.8

受控文件

3.机械强度
Mechanical Strength

$$F \geq \frac{N}{n}$$




受控文件

The following Page(s) are related to Miscellaneous-02. The next supplement, if applicable, will be identified with a new Supplement Page Heading.

Customer:	WSTZ0	Customer P/N:	EP07-003864
-----------	-------	---------------	-------------

1.Mechanical Dimension:



Item	Spec.(mm)	Typ.(mm)	Item	Spec.(mm)	Typ.(mm)
A	9.5 MAX	9.04	F		
B	6.0 MAX	5.48	G		
C	5.0 MAX	4.55	H		
D			I		
E			J		

Notes:

2.1 Marking : ●472

3L P/N :	SMTLF3922P-472N-0.5A	Rev.	XA	Date:	2023/04/14
----------	----------------------	------	----	-------	------------

Customer:	WSTZ0	Customer P/N:	EP07-003864
------------------	-------	----------------------	-------------

2. Electrical Characteristics :

Test Item	Specifications	Typ.	Test Instrument :
L1;L2	4.7mH +50%-30%	4.90mH	HP4284A PRECISION LCR METER
Test Freq.	@100kHz 1.0V		HP4284A PRECISION LCR METER
Leakage	0.6uH MAX	0.33uH	HP4284A PRECISION LCR METER
Test Freq.	@100kHz 1.0V		HP4284A PRECISION LCR METER
DCR1;DCR2	0.75Ω MAX	0.658Ω	CHENHWA 502 OHM METER
R.Current	0.5A MAX (@125°C)		HP4284A WITH HP42841A CURRENT SOURCE
Hi-pot	@DC 125V 2mA 2 Sec (Between coil and coil)		7142AC/DCWITHSTAND/INSULATION TESTER 7142AC/DCWITHSTAND/INSULATION TESTER
Turns	45Tx2(INSIDE) REF		
Ope.Temp.	-40 TO 125°C		HC-D3M TEMP. & HUMIDITY CHAMBER
Weight	0.32g/pcs		

3. Material List:

Item	Material (Or Equal)	Supplier (Or Equal)	UL No.& Temp.
CORE	T 3.9X2X2 N10 P	ENCORE	
WIRE	P180 G2 0.10	Elekatrisola company limited	E258243 180°C
WIRE	P180 G2 0.10 RED	Elekatrisola company limited	E258243 180°C
EPOXY	EPOXY RTV1-2577	Sil-More Industrial Ltd.	E81611
SOLDER	PURE SOLDER	THOUSAND ISLAND METAL FOIL CO.	
BASE	BAS K5 4P	SUMIMOTO BAKELINE CO LTD	E41429

Notes: 1. Leakage: Test L1 short connected L2, or Test L2 short connected L1.
2. Rated voltage 80V (REF).

3L P/N :	SMTLF3922P-472N-0.5A	Rev.	XA	Date:	2023/04/14
-----------------	----------------------	-------------	----	--------------	------------













NETWORK CAMERA, TNV-C8014RM

PoE (48V ) 0.15A

M/C: TNV-C8014RM/KEX Fac.ID:D



DATE S/N: XXXXXXXXXXXXXXXXX

MAC ADDRESS: XX-XX-XX-XX-XX-XX

CAN ICES-3(A)/NMB-3(A)

HANWHA VISION CO.,LTD.

MADE IN KOREA

Rainproof/ Étanche

IP66

